



Red Hat OpenStack Platform 13

Fujitsu ETERNUS Back End Guide

A guide to using a Fujitsu ETERNUS back end in a Red Hat OpenStack Platform environment

Red Hat OpenStack Platform 13 Fujitsu ETERNUS Back End Guide

A guide to using a Fujitsu ETERNUS back end in a Red Hat OpenStack Platform environment

OpenStack Team
rhos-docs@redhat.com

Legal Notice

Copyright © 2023 Red Hat, Inc.

The text of and illustrations in this document are licensed by Red Hat under a Creative Commons Attribution–Share Alike 3.0 Unported license ("CC-BY-SA"). An explanation of CC-BY-SA is available at

<http://creativecommons.org/licenses/by-sa/3.0/>

. In accordance with CC-BY-SA, if you distribute this document or an adaptation of it, you must provide the URL for the original version.

Red Hat, as the licensor of this document, waives the right to enforce, and agrees not to assert, Section 4d of CC-BY-SA to the fullest extent permitted by applicable law.

Red Hat, Red Hat Enterprise Linux, the Shadowman logo, the Red Hat logo, JBoss, OpenShift, Fedora, the Infinity logo, and RHCE are trademarks of Red Hat, Inc., registered in the United States and other countries.

Linux[®] is the registered trademark of Linus Torvalds in the United States and other countries.

Java[®] is a registered trademark of Oracle and/or its affiliates.

XFS[®] is a trademark of Silicon Graphics International Corp. or its subsidiaries in the United States and/or other countries.

MySQL[®] is a registered trademark of MySQL AB in the United States, the European Union and other countries.

Node.js[®] is an official trademark of Joyent. Red Hat is not formally related to or endorsed by the official Joyent Node.js open source or commercial project.

The OpenStack[®] Word Mark and OpenStack logo are either registered trademarks/service marks or trademarks/service marks of the OpenStack Foundation, in the United States and other countries and are used with the OpenStack Foundation's permission. We are not affiliated with, endorsed or sponsored by the OpenStack Foundation, or the OpenStack community.

All other trademarks are the property of their respective owners.

Abstract

This document describes how to configure Red Hat OpenStack Platform 13 to use a Fujitsu ETERNUS Disk Storage System as a back end.

Table of Contents

MAKING OPEN SOURCE MORE INCLUSIVE	3
CHAPTER 1. INTRODUCTION	4
CHAPTER 2. CONFIGURING THE FUJITSU ETERNUS DEVICE	5
CHAPTER 3. PREPARING THE FUJITSU ETERNUS HEAT TEMPLATE	7
3.1. CREATING DRIVER DEFINITIONS FOR EACH FUJITSU ETERNUS BACK END	8
3.2. EXAMPLE FUJITSU ETERNUS HEAT TEMPLATE	9
CHAPTER 4. CREATING THE FUJITSU ETERNUS ENVIRONMENT FILE	11
CHAPTER 5. DEPLOYING THE CONFIGURED FUJITSU ETERNUS BACK ENDS	13
CHAPTER 6. TESTING YOUR FUJITSU ETERNUS CONFIGURATION	14

MAKING OPEN SOURCE MORE INCLUSIVE

Red Hat is committed to replacing problematic language in our code, documentation, and web properties. We are beginning with these four terms: master, slave, blacklist, and whitelist. Because of the enormity of this endeavor, these changes will be implemented gradually over several upcoming releases. For more details, see [our CTO Chris Wright's message](#).


CHAPTER 1. INTRODUCTION

This document describes how to configure Red Hat OpenStack Platform to use a Fujitsu ETERNUS Disk Storage System as a back end for the Block Storage service. The document covers how to define a Fibre Channel and iSCSI back end provided by an ETERNUS device on an overcloud deployment. This process involves defining both back ends as a **custom back end** for the Block Storage service. By default, Controller nodes contain the Block Storage service.

Prerequisites

- A Red Hat OpenStack Platform overcloud deployed through director with container **registry.connect.redhat.com/fujitsu/rhosp13-fujitsu-cinder-volume-161** of Fujitsu Plugin. For more information, see [Deploying a vendor plugin](#).
- You intend to use only Fujitsu ETERNUS Disk Storage System devices and drivers for Block Storage back ends.
- You can use the *director installation user*, that you create with the overcloud deployment. For more information, see [Creating the Stack User](#) from [Director Installation and Usage](#).
- You have access to an **Admin** account on the ETERNUS device through the ETERNUS Web GUI or CLI.

Red Hat supports using Fibre Channel or iSCSI interfaces, and the respective drivers and settings, with a Fujitsu ETERNUS device.



NOTE

For more information about defining a custom back end, see [Custom Block Storage Back End Deployment Guide](#).

CHAPTER 2. CONFIGURING THE FUJITSU ETERNUS DEVICE

Configure storage pools and ports on the device before you define the Fujitsu ETERNUS device as a Block Storage back end. Consult your device documentation for details on each step:

Procedure

1. Configure a LAN connection between the Controller nodes that host the Block Storage service and the MNT ports of the ETERNUS device.
2. Configure a SAN connection between the Compute nodes and CA ports of the ETERNUS device.
3. Log in to the ETERNUS device using an account with the **Admin** role.
4. Enable the SMI-S of ETERNUS DX.
5. Set the SSH key
6. Add a user account with **software** role.
7. Register an **Advanced Copy Feature** license and configure the copy table size.
8. Create a storage pool for volumes. You use this pool later in the **EternusPool** setting in [Section 3.1, "Creating driver definitions for each Fujitsu ETERNUS back end"](#) .
9. Optional: Create a separate storage pool for volume snapshots. This pool represents the **EternusSnapPool** setting in [Section 3.1, "Creating driver definitions for each Fujitsu ETERNUS back end"](#).
10. Optional: Create a **Snap Data Pool Volume (SDPV)** to enable Snap Data Pool (SDP) for the **create a snapshot** function.

TIP

Skip this step if you use a Thin Provision Pool for **EternusSnapPool**.

11. Configure **storage ports** to be used by the Block Storage service.
12. Set the **storage ports** ports to **CA** mode.
13. To enable **host-affinity** for the storage ports, enter the following command from the ETERNUS CLI for each port:


```
set <PROTO>-parameters -host-affinity enable -port <CM#> <CA#> <PORT>
```

- Replace <PROTO> with the storage protocol, such as **fc** or **iscsi**.
- Replace <CM#> and <CA#> with the name of the controller enclosure where the port is located.
- Replace <PORT> with the port number.

14. Use the following commands to generate the SSH key on the undercloud, and upload the **eternus.ietf** file to the ETERNUS device.

■

```
ssh-keygen -t rsa -N "" -f ./eternus  
ssh-keygen -e -f ./eternus.pub > ./eternus.ietf
```



NOTE

Save the **eternus** file for later use. For security reasons, do not copy or move it from the undercloud or overcloud.

CHAPTER 3. PREPARING THE FUJITSU ETERNUS HEAT TEMPLATE

To ensure that your settings persist throughout future updates to the Red Hat OpenStack Platform overcloud, perform all service configuration during deployment through director.

Include the following configuration on the Controller node of the ETERNUS back end that hosts the Block Storage service:

- You include an XML configuration file for the driver settings of each back end.
- You include an SSH server key to communicate with ETERNUS device.

You can orchestrate both tasks with director using a heat template. For more information about the syntax of director heat templates, see [Understanding Heat Templates](#) in the *Advanced Overcloud Guide*.

The following template, **eternus-temp.yaml**, outlines the basic syntax for the required heat template.

eternus-temp.yaml

```
heat_template_version: 2014-10-16

description: >
  Add XML configuration file for the driver settings of each back end

parameters:
  server:
    type: string

resources:
  EternusSetup: # 1
    type: OS::Heat::SoftwareConfig
    properties:
      group: script
      config: | # 2
        #!/bin/bash
        # 3

  ExtraPreDeployment:
    type: OS::Heat::SoftwareDeployment
    properties:
      config: {get_resource: EternusSetup}
      server: {get_param: server}
      actions: ['CREATE','UPDATE']
```

- 1 The **EternusSetup** section contains the resource that orchestrates the tasks on the Controller node.
- 2 The **config** section contains the commands to run on the Controller node.
- 3 Copy the private key information to each Controller node where the Block Storage service is hosted, and add commands to create the XML configuration files for the driver settings of each back end in [Section 3.1, “Creating driver definitions for each Fujitsu ETERNUS back end”](#) .

Store this file in the custom heat template directory on the director node, `/home/stack/templates/`.

3.1. CREATING DRIVER DEFINITIONS FOR EACH FUJITSU ETERNUS BACK END

Define driver settings for each ETERNUS back end on separate XML files, not the Block Storage configuration file `/etc/cinder/cinder.conf`. Ensure that each back end has an XML file, with the following settings:

EternusIP

IP address of the SMI-S connection of the ETERNUS device. Use the IP address of the MNT port of the device.

EternusPort

Port number for the SMI-S connection port of the ETERNUS device.

EternusUser

User name of **software** role for the connection **EternusIP**.

EternusPassword

Corresponding password of **EternusUser** on **EternusIP**.

EternusPool

Name of the storage pool for the volumes from [Chapter 2, Configuring the Fujitsu ETERNUS device](#). Use the pool RAID Group name or TPP name in the ETERNUS device.

EternusSnapPool

Name of the storage pool for the volume snapshots from [Chapter 2, Configuring the Fujitsu ETERNUS device](#). Use the pool RAID Group name in the ETERNUS device. If you did not create a different pool for snapshots, use the same value as **EternusPool**.

Define a Fibre Channel configuration with the following xml example:

eternus-fc.xml

```
<?xml version='1.0' encoding='UTF-8'?>
<FUJITSU>
<EternusIP>0.0.0.0</EternusIP>
<EternusPort>5988</EternusPort>
<EternusUser>smisuser</EternusUser>
<EternusPassword>smispassword</EternusPassword>
<EternusPool>raid5_0001</EternusPool>
<EternusSnapPool>raid5_0001</EternusSnapPool>
</FUJITSU>
```

Define an iSCSI configuration with the following xml example:

eternus-iscsi.xml

```
<?xml version='1.0' encoding='UTF-8'?>
<FUJITSU>
<EternusIP>0.0.0.0</EternusIP>
<EternusPort>5988</EternusPort>
<EternusUser>smisuser</EternusUser>
<EternusPassword>smispassword</EternusPassword>
```

```
<EternusPool>raid5_0001</EternusPool>
<EternusSnapPool>raid5_0001</EternusSnapPool>
</FUJITSU>
```

To orchestrate the creation of these XML files, include bash commands in the **config** section of the **EternusSetup** resource in the `/home/stack/templates/eternus-temp.yaml` file from [Chapter 3, *Preparing the Fujitsu ETERNUS heat template*](#). Orchestrate the creation of **eternus-fc.xml** and **eternus-iscsi.xml** with the following example command:

```
sudo cat > /etc/cinder/eternus-fc.xml <<EOF
<?xml version='1.0' encoding='UTF-8'?>
<FUJITSU>
<EternusIP>0.0.0.0</EternusIP>
<EternusPort>5988</EternusPort>
<EternusUser>smisuser</EternusUser>
<EternusPassword>smispassword</EternusPassword>
<EternusPool>raid5_0001</EternusPool>
<EternusSnapPool>raid5_0001</EternusSnapPool>
</FUJITSU>
EOF
```

```
sudo cat > /etc/cinder/eternus-iscsi.xml <<EOF
<?xml version='1.0' encoding='UTF-8'?>
<FUJITSU>
<EternusIP>0.0.0.0</EternusIP>
<EternusPort>5988</EternusPort>
<EternusUser>smisuser</EternusUser>
<EternusPassword>smispassword</EternusPassword>
<EternusPool>raid5_0001</EternusPool>
<EternusSnapPool>raid5_0001</EternusSnapPool>
</FUJITSU>
EOF
```

Use the **sudo cat** command to create the required amount of XML configuration files.

Set the ownership and permissions of these XML files for the **cinder** user and group.

```
sudo chown cinder:cinder /etc/cinder/eternus-*.xml
sudo chmod 0600 /etc/cinder/eternus-*.xml
```

For an example of a completed heat template, see [Section 3.2, “Example Fujitsu ETERNUS heat template”](#).

3.2. EXAMPLE FUJITSU ETERNUS HEAT TEMPLATE

The following `/home/stack/templates/eternus-temp.yaml` file contains the necessary parameters for declaring the example XML configuration files, such as **eternus-fc.xml** and **eternus-iscsi.xml**:

`/home/stack/templates/eternus-temp.yaml`

```
heat_template_version: 2014-10-16

description: >
  Add XML configuration file for the driver settings of each back end
```

```

parameters:
  server:
    type: string

resources:
  EternusSetup:
    type: OS::Heat::SoftwareConfig
    properties:
      group: script
      config: |
        #!/bin/bash
        sudo cat > /etc/cinder/eternus-fc.xml <<EOF
        <?xml version='1.0' encoding='UTF-8'?>
        <FUJITSU>
        <EternusIP>0.0.0.0</EternusIP>
        <EternusPort>5988</EternusPort>
        <EternusUser>smisuser</EternusUser>
        <EternusPassword>smispassword</EternusPassword>
        <EternusPool>raid5_0001</EternusPool>
        <EternusSnapPool>raid5_0001</EternusSnapPool>
        </FUJITSU>
        EOF
        sudo cat > /etc/cinder/eternus-iscsi.xml <<EOF
        <?xml version='1.0' encoding='UTF-8'?>
        <FUJITSU>
        <EternusIP>0.0.0.0</EternusIP>
        <EternusPort>5988</EternusPort>
        <EternusUser>smisuser</EternusUser>
        <EternusPassword>smispassword</EternusPassword>
        <EternusPool>raid5_0001</EternusPool>
        <EternusSnapPool>raid5_0001</EternusSnapPool>
        </FUJITSU>
        EOF
        sudo cat > /etc/cinder/eternus <<EOF
        -----BEGIN RSA PRIVATE KEY----- # 1
        MIIEpAIBAACAQEA5yMqonpfniu+11PJ8qdWZpcf0d4UcHj2uyE7ou7vcZUQ1Cq
        s5Q5pjkCgYAXITlpfOYA8jvLgc7vMEa/ZbhUgAPIYlisxbffmRsBWYJSt9gwHpcW
        hvaWo6VD/iUKZ3bOcmK0buUwBdFUt5s9B8mXbYsX6bWovlVkyu8DzQfpDiPnV6C8
        ...
        IB+46ldmCUO0DaciuEz5/KQd4AXBNdTOss2od6OzihDJXKjBwPyP1g==
        -----END RSA PRIVATE KEY-----
        EOF

  ExtraPreDeployment:
    type: OS::Heat::SoftwareDeployment
    properties:
      config: {get_resource: EternusSetup}
      server: {get_param: server}
      actions: [CREATE,UPDATE]

```

1 **Private Key** information in **eternus** file generated on the undercloud in [Chapter 2, Configuring the Fujitsu ETERNUS device](#).

CHAPTER 4. CREATING THE FUJITSU ETERNUS ENVIRONMENT FILE

The environment file contains the settings for each back end that you want to define, and other relevant settings. For more information about environment files, see [Environment Files](#) in the *Advanced Overcloud Customization* guide.

In addition, the environment file registers the heat template that you created earlier in [Chapter 3, Preparing the Fujitsu ETERNUS heat template](#). The installation and echo commands defined in the heat template run on the appropriate nodes during deployment.

The following example environment file contains the necessary sections for defining an ETERNUS device as a Block Storage back end. It also creates the back end definitions for each corresponding XML file orchestrated in [Section 3.1, “Creating driver definitions for each Fujitsu ETERNUS back end”](#), and [Section 3.2, “Example Fujitsu ETERNUS heat template”](#).

eternusbackend-env.yaml

```
resource_registry:
  OS::TripleO::NodeExtraConfig: /home/stack/templates/eternus-temp.yaml # 1

parameter_defaults: # 2
  CinderEnableIscsiBackend: false
  CinderEnableRbdBackend: false
  CinderEnableNfsBackend: false
  NovaEnableRbdBackend: false
  GlanceBackend: file # 3
  controllerExtraConfig: # 4
    cinder::config::cinder_config:
      FJFC/volume_driver: # 5
        value: cinder.volume.drivers.fujitsu.eternus_dx.eternus_dx_fc.FJDXFCDriver
      FJFC/cinder_eternus_config_file: # 6
        value: /etc/cinder/eternus-fc.xml
      FJFC/volume_backend_name: # 7
        value: FJFC
      FJFC/fujitsu_private_key_path:
        value: /etc/cinder/eternus
      FJISCSI/volume_driver: # 8
        value: cinder.volume.drivers.fujitsu.eternus_dx.eternus_dx_iscsi.FJDXISCSIDriver
      FJISCSI/cinder_eternus_config_file:
        value: /etc/cinder/eternus-iscsi.xml
      FJISCSI/volume_backend_name:
        value: FJISCSI
      FJISCSI/fujitsu_private_key_path:
        value: /etc/cinder/eternus
    cinder_user_enabled_backends: ['FJFC','FJISCSI'] # 9
  CinderVolumeOptVolumes: # 10
    - /etc/cinder/eternus-iscsi.xml:/etc/cinder/eternus-iscsi.xml:ro
    - /etc/cinder/eternus-fc.xml:/etc/cinder/eternus-fc.xml:ro
    - /etc/cinder/eternus:/etc/cinder/eternus:ro
```

- 1 Define custom settings for all nodes before the core Puppet configuration with **NodeExtraConfig**. This ensures the following configuration when the Block Storage service deploys on the overcloud:

- The XML configuration files for each back end are present.
 - The private key is generated.
- 2 Set the following parameters to **false** to disable the other back end types:
 - **CinderEnableIscsiBackend**: other iSCSI back ends.
 - **CinderEnableRbdBackend**: Red Hat Ceph Storage.
 - **CinderEnableNfsBackend**: NFS.
 - **NovaEnableRbdBackend**: ephemeral Red Hat Ceph Storage.
 - 3 Define the Image service image storage settings with the **GlanceBackend** parameter. The following values are supported:
 - **file** stores images on **/var/lib/glance/images** on each Controller node.
 - **swift** uses the Object Storage service for image storage.
 - **cinder** uses the Block Storage service for image storage.
 - 4 Define custom settings for all Controller nodes with **controllerExtraConfig**. The **cinder::config::cinder_config** class is for the Block Storage service. Director stores these back end settings in the **/etc/cinder/cinder.conf** file of each node.
 - 5 Configure a back end definition named **FJFC** with the **FJFC/** string, and declare the **volume_driver** parameter under that back end definition. Set the Fibre Channel ETERNUS driver for the back end with the **volume_driver** parameter, for example **cinder.volume.drivers.fujitsu.eternus_dx.eternus_dx_fc.FJDXFCDriver**.
 - 6 Set the path to the XML configuration file that the driver uses for the back end with **cinder_eternus_config_file**. Orchestrate the creation of **/etc/cinder/eternus-fc.xml** through the heat template, such as, **/home/stack/templates/eternus-temp.yaml**.
 - 7 The **volume_backend_name** is the name that the Block Storage service uses to enable the back end.
 - 8 Configure a new back end definition with the **FJISCSI/** string. Set the iSCSI ETERNUS driver for the back end with the **volume_driver** parameter, for example **cinder.volume.drivers.fujitsu.eternus_dx.eternus_dx_iscsi.FJDXISCSIDriver**.
 - 9 Set and enable custom back ends with the **cinder_user_enabled_backends** class. Use this class for user-enabled back ends only, such as those defined in the **cinder::config::cinder_config** class.
 - 10 Make custom configuration files on the host available to a cinder-volume service running in a container with **CinderVolumeOptVolumes**.

After creating the environment file, you can deploy your configuration. For more information about the environment file **/home/stack/templates/eternusbackend-env.yaml**, see [Chapter 5, Deploying the configured Fujitsu ETERNUS back ends](#).

CHAPTER 5. DEPLOYING THE CONFIGURED FUJITSU ETERNUS BACK ENDS

After you create the `eternusbackend-env.yaml` file in `/home/stack/templates/`, complete the following steps:

Procedure

1. Log in as the **stack** user.
2. Deploy the back end configuration with the following command:

```
$ openstack overcloud deploy --templates \  
-e [your environment files] \  
-e /home/stack/templates/eternusbackend-env.yaml
```



IMPORTANT

If you passed any extra environment files when you created the overcloud, pass them again here by using the **-e** option to avoid making undesired changes to the overcloud. For more information, see [Modifying the Overcloud Environment](#) in the *Director Installation and Usage* guide.

Test the back end after director orchestration is complete. See [Chapter 6, Testing your Fujitsu ETERNUS configuration](#).

CHAPTER 6. TESTING YOUR FUJITSU ETERNUS CONFIGURATION

After you configure the Block Storage service to use the new ETERNUS back ends, declare a **volume type** for each back end. Use volume types to specify which back end to use when you create new volumes.

- Create a Fibre Channel back end and map it to the respective back end with the following commands:

```
# cinder type-create FJFC
# cinder type-key FJFC set volume_backend_name=FJFC
```

- Create an iSCSI back end and map it to the respective back end with the following commands:

```
# cinder type-create FJISCSI
# cinder type-key FJISCSI volume_backend_name=FJISCSI
```

For more information about volume types, see [Chapter 4, *Creating the Fujitsu ETERNUS environment file*](#):

- Create a 1GB iSCSI volume named **test_iscsi** to verify your configuration:

```
# cinder create --volume_type FJISCSI --display_name test_iscsi 1
```

- Test the Fibre Channel back end:

```
# cinder create --volume_type FJFC --display_name test_fc 1
```